#### Click START

Select Settings



## Select Connections



## Select WIFI



### Select Profile

Select Scan

Summit Client Utility	🔉 🏹 📢 🔁 12:58
Edit Profile: Default	SDC
New Rename	Delete Scan
Radio:	
SSID	tsunami
Client Name	
Tx Power	
Encryption:	EAP Type:
None 💽	None 💽
WEP keys/PSKs	Credentials
Save Changes:	Commit
Main Profile Status	Diags Global
	E) OK

Select your SSID network Click Configure

Summit Client Util	ity 🔉	Y_x	€œı	3:01
	_			l
SSID	F	SSI	Secure	$\sim$
GR-Staff	-	65	true	===
Meniga-Office	-	91	true	
FariceGuest	-	72	false	
HP-Print-20-Office	ei -	74	true	
dkStaging		60	true	
dkGuest	-	85	false	
OR-Guests	-	66	false	
OR-Mobile	-	66	true	
Configure			Refresh	
				_
			6	IK)
			C	

Click Yes

Summit C	lient Utility 🤉	₽ Yx I	€ @ 1:	3:18
SSID		RSSI	Secure	$\land$
scu				
?	Create a new SSID: dkSt Encryption EAP Type:	w profik aging : WPA2 None	e? 2 PSK	
4	You may be enter credentials o	promp or keys.	ted to	ľ
Yes	No		ancel	ſ
•		)	0	K)

# Select keyboard Icon

Summit Client ( For Passphras For PSK, ente	Utility 🤉 e, enter er 64 Hex	• Y ← € 13:19 8-63 chars chars
I		
ОК		Cancel
		ł
$\bigcirc$		OK

Enter Passphrase

Click OK

Summit Client Utility 📯 🏆 📢 🔁 13:20
For Passphrase, enter 8-63 chars For PSK, enter 64 Hex chars
OK Cancel
$\frac{123}{1} \frac{1}{2} \frac{3}{3} \frac{4}{5} \frac{5}{6} \frac{6}{7} \frac{8}{9} \frac{9}{0} \frac{1}{2} = \blacksquare$
$\frac{\operatorname{Sinc}[2] \times [2] \times [2] \times [3]}{\operatorname{Ctl}[\operatorname{au}] \times [1]} \xrightarrow{[4]} [3] \operatorname{Sinc}[2] \times [2] \times [3]$
🖅 🖾 🐼

**Click Commit** 

Summit Client Utility	유• 🏆 📢 🖻 13:22
Profile: dkStaging	🗷 SDC
New Rename	Delete Scan
Radio:	
SSID	dkStaging
Client Name	
Tx Power	
Encryption:	EAP Type:
WPA2-PSK 💽	None 💽
WEP keys/PSKs	Credentials
Save Changes:	Commit
Main Profile Status	Diags Global
	СК

### Select Main

Summit Client Utility	፼ 🖓 📢 🕑 13:24
Edit Profile: dkStaging	SDC
New Rename	Delete Scan
Radio:	
SSID	dkStaging
Client Name	
Ty Power	
Encryption:	EAP Type:
WPA2-PSK	None 💌
WEP keys/PSKs	Credentials
Save Changes:	Commit
Main Profile Status	Diags Global
	ОК

Select Active profile

Summit Clien	t Utility 🖇	₽• Ҡ €	
	•		
CI IN AN	<b>41T</b>		
DATA COMMUN	CATIONS	Disable	Radio
Active Profile:	Default		
Status	ThirdPar	tyConfig	
Radio Type:	dkStagir	10	
Reg. Domain:	Worldw	ride.	
Auto Profile	$\bigcirc 0$	Off	List
Drivor: v2.02	21 9		22
Driver. v5.05	.21 5	0. 15.05	.22
		Abou	t SCU
		-	_
Main Profile	Status D	iags Globa	al
			OK
	C		$\bigcirc$

Profile is now active! Select Status

Summit Client Utility 👷 🏹 📢 🔁 14:04
Disable Radio
Active Profile dkStaging
Status: Associated
Radio Type: BGN
Reg. Domain: Worldwide
Auto Profile: 🔿 On 🖲 Off 🛛 List
Driver: v3.03.21 SCU: v3.03.22
About SCU
Main Profile Status Diags Global

Status Associated ?

IP?

Well then the Network should now be configured and Active!



Finished now click OK

